



## FEATURES

- AC ONLY OR SELF-POWERED MODELS
- 120 OR 277 VAC INPUT ON AC ONLY
- 120/277 VAC SELECTABLE INPUT ON EMERGENCY OPERATION SIGNS
- TWO 15 WATT AC LAMPS
- TWO 4 WATT DC LAMPS IN EMERGENCY MODE
- MEETS NFPA LIFE SAFETY, OSHA, NEC, LOCAL AND STATE CODES

REX Fully Recessed

.82 pf LED option only

## Application

High-Lites REX Series exits are designed for fully recessed mounting. With the vandal resistant Lexan® front, it is ideal for low level exit mounting to meet the California code.

High-Lites Rex Exit can be used as a remote sign by adding the LVE option to the AC only unit. It can then be powered by any DC equipment that has remote capability and properly selected output voltage.

## Unit Selection Chart

Series	Model	Number of Faces	Color of Face
<b>AC Only</b> REX	REX	Single Face Recessed Only	- R - (Red)
<b>Emergency Operation</b> BP-REX Pure Lead	BP-REX		- G - (Green)

## Options

Add	Description
-B	Black Body & Stencil
-BS	Black Body And Silver Stencil
-FA	Fire Alarm Interface
-1CF5	Single 5 Watt PL Type Lamp (120 VAC)
-2CF5	Double 5 Watt PL Type Lamps (120 VAC)
-SW	Special Wording (See Custom Signage Page)
-LVE-1	Twin 6 volt socket and lamp for REX
-LVE-2	Twin 12 volt socket and lamp for REX
-LVE-3	Twin 24 volt socket and lamp for REX
-277V	277 volt option for REX (AC only)
-LED	Direct View LEDS
-XL-100	2 LED Lamps (2 required)

## Ordering Example:

Model BP-REX - R - FA

Color \_\_\_\_\_

Option \_\_\_\_\_

